Texas Electronics

"Relied on Worldwide in the Most Extreme Conditions"



Rain Gauge LCD Counter

BC-200

Compact remote enclosed water-proof counter used to collect data when performing a tipping bucket rain gauge field calibration.

The counter is connected to the switch contact inside a tipping bucket rain gauge as its being calibrated in the field and the tipping bucket count is saved into a historical file.

- Internal 15+ year battery
- Waterproof enclosure
- Reflective LCD Display with 8 Large (8mm) digits
- Front panel reset button
- Waterproof front reset button

Operating Instructions

- Disconnect the rain gauge from the data logger or other measuring device
- Connect the two wires from the LCD counter to the rain gauge
- Each tip of the rain gauge bucket will increment one count
- Push the red button to reset count